

**The PowerPact Advantage**

- **Proven Performance:** Industry-leading circuit breaker innovation and protection for heavy-duty commercial and industrial applications.
- **Flexible:** Full range of molded case circuit breakers from 15 A to 3000 A, delivering the ratings, configurations, and operators for your unique applications.
- **Simple:** Common catalog numbers, standardized ratings, and a full range of field-installable accessories make product selection, installation and maintenance easier than ever.
- **Common Design Features:** Mounting holes, door trim, and handle accessories



**Table 7.35: PowerPact Interrupting Ratings**

Voltage	Interrupting Rating					
	B	D	G	J	K	L
240 Vac	10 kA	25 kA	65 kA	100 kA	65 kA	125 kA
480 Vac		18 kA	35 kA	65 kA	65 kA ▲	100 kA
600 Vac		14 kA	18 kA	25 kA	65 kA ▲	50 kA

▲ P-frame K interrupting is 50 kA at 480 and 600 Vac.

**Table 7.36: Common Catalog Numbering System**

Frame	Rating	Termination	Poles	Voltage	Amperage			Suffix Code		Suffix Code	
					1	5	0	A	B	S	A
H	G	L	3	6	1	5	0	A	B	S	A

  

Frame Designation	Interrupting Rating	Terminations
G 100A Frame	240 Vac 10 kA	A I-Line
H 150 A Frame	480 Vac 18 kA	L Lugs on Both Ends
J 250 A Frame	600 Vac 25 kA	F Bus Bar (No Lugs)
Q 250 A Frame	600 Vac 18 kA	M Lugs Line Side Only
D 600 A Frame	600 Vac 35 kA	P Lugs Load End Only
M 800 A Frame	600 Vac 100 kA	N Plug-in
P 1200 A Frame	600 Vac 65 kA	D Drawout
R 3000 A Frame	600 Vac 125 kA	S Rear Connected Studs

■ For amperage of M-, P- or R-frame circuit breakers, add a zero to the three amperage digits; for example, 120 = 1200 A.

<b>Description</b> . . . . .	<b>Page</b>
H- and J-Frame Circuit Breakers . . . . .	7-22
H- and J-Frame Circuit Breakers . . . . .	7-23
G- and Q-Frame Circuit Breakers . . . . .	7-24
D- and M-Frame Circuit Breakers . . . . .	7-25
P-Frame Circuit Breakers . . . . .	7-26
R-Frame Circuit Breakers . . . . .	7-27
PowerPact® H- and J-Frame Electronic Motor Circuit Protectors . . . . .	7-28
Mag-Gard® Motor Circuit Protectors (MCP) . . . . .	7-30
Automatic Switches . . . . .	7-33
500 Vdc Circuit Breakers . . . . .	7-34
Mission Critical Circuit Breakers . . . . .	7-35
PowerPact® Circuit Breaker Accessories . . . . .	7-36
Motor Operators and Rotary Handles . . . . .	7-37
Locks, Installation Accessories, and Rear Connections . . . . .	7-38
Mechanical Lugs . . . . .	7-38
Compression Lugs and Power Distribution Connectors (PDC) . . . . .	7-40
Terminal Nuts, Terminal Pads, Terminal Shields and Accessories . . . . .	7-41
Plug-In and Drawout Mountings . . . . .	7-42
Micrologic® Electronic Trip Units . . . . .	7-43
Micrologic Trip Unit Accessories . . . . .	7-44