

# analog ammeter AMP - 3 In without dial - 72 x 72 mm

16003

#### Main

Range	PowerLogic	
Device Short Name	AMP	
Product Or Component Type	Ammeter	
Device Application	Motor	
Range Compatibility	Prisma Prisma P door Prisma Prisma G door	
Technology Type	Ferromagnetic	
Scale Type	62 mm over 90°	
Mounting Support	Front face	

### Complementary

Type Of Measurement	Current
Accuracy Class	Class 1.5
Power Consumption In Va	1.1 VA
Power Consumption In Va	1.1 VA
Overload Withstand	1.2 In, permanently 10 In, 5 s
Device Mounting	Flush
Operating Position	30°/vertical
Width	72 mm
Height	72 mm
Depth	75 mm
Temperature Drift	+/- 0.003 %/°C

#### **Environment**

Standards	IEC 61010-1 IEC 61000-4 IEC 60051-1
Ip Degree Of Protection	IP52
Ambient Air Temperature For Operation	-2550 °C
Reference Temperature	23 °C

#### **Packing Units**

Unit Type Of Package 1 PCE

Number Of Units In Package 1	1
Package 1 Height	10.0 cm
Package 1 Width	8.5 cm
Package 1 Length	9.0 cm
Package 1 Weight	191.0 g
Unit Type Of Package 2	S03
Number Of Units In Package 2	33
Package 2 Height	30.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	6.757 kg

## **Contractual warranty**

Warranty 18 months

#### Sustainability

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

#### Well-being performance

<b>7 1 1 1 1 1 1 1 1 1 1</b>	
Mercury Free	
Rohs Exemption Information	Yes
Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant with Exemptions
China Rohs Regulation	China RoHS declaration
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins