Product data sheet

Specifications



Mureva FIX - instaclip for Ø16 and 20 mm conduits

ENN45020

Main

Range Of Product	Mureva
Product Or Component Type	Conduit support
Colour	Grey (RAL 7035)
Quantity Per Package	100 pieces

Complementary

Accessory / Separate Part Category	Installation accessory	
Condition Of Use	Indoor	
Tube Diameter	16 mm 20 mm	
Material	PA (polyamide) 6/6	
Fixing Mode	By screw By Murafix plug	
Net Weight	0.002 kg	

Environment

Operating Temperature -5...60 °C

Packing Units

V	
Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	2.0 cm
Package 1 Width	2.5 cm
Package 1 Length	7.0 cm
Package 1 Weight	2.0 g
Unit Type Of Package 2	BB1
Number Of Units In Package 2	100
Package 2 Height	7.5 cm
Package 2 Width	12.5 cm
Package 2 Length	19.0 cm
Package 2 Weight	224.0 g
Unit Type Of Package 3	CAR
Number Of Units In Package 3	2000

Package 3 Height	29.0 cm
Package 3 Width	39.5 cm
Package 3 Length	40.0 cm
Package 3 Weight	4.875 kg

Contractual warranty

Warranty

18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



Fa

Transparency RoHS/REACh

Well-being performance

Reach Free Of Svhc

Toxic Heavy Metal Free	
Mercury Free	
Rohs Exemption Information	Yes

Certifications & Standards

Reach Regulation	REACh Declaration
Eu Rohs Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration
China Rohs Regulation	China RoHS declaration Pro-active China RoHS declaration (out of China RoHS legal scope)
Environmental Disclosure	Product Environmental Profile
Circularity Profile	No need of specific recycling operations