

Lisse - switched socket - without instructions - 13 A - 230 V - 1 gang - white

GGBL3010NIS

Main

Range	Lisse
Aesthetic Name	White moulded
Product Or Component Type	Switched socket
Device Presentation	Complete product
Outlet Standard	British
Colour Tint	Matt white
Quantity Per Set	Set of 1
Type Of Packing	Bag

Complementary

Switch Function	1-pole
Rated Current	13 A at 250 V AC 50 Hz
Actuator	Rocker
Number Of Gangs	1 gang
Pilot Light	without LED
Fixing Mode	By screws
Connections - Terminals	Screw terminals
Material	Urea (carbamide)
Type Of Installation	Indoor
Depth	33 mm
Width	87 mm
Height	87 mm
Net Weight	0.092 kg

Environment

Standards	BS 1363-2
Ip Degree Of Protection	IP20

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	2.500 cm

Package 1 Width	8.700 cm
Package 1 Length	8.700 cm
Package 1 Weight	92.000 g
Unit Type Of Package 2	BB1
Number Of Units In Package 2	10
Package 2 Height	9.200 cm
Package 2 Width	15.500 cm
Package 2 Length	18.100 cm
Package 2 Weight	1.105 kg
Unit Type Of Package 3	CAR
Number Of Units In Package 3	200
Package 3 Height	33.000 cm
Package 3 Width	38.000 cm
Package 3 Length	48.000 cm
Package 3 Weight	22.220 kg

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



RoHS/REACh

Well-being performance



Rohs Exemption Information

Yes

Certifications & Standards

Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant
	EU RoHS Declaration
China Rohs Regulation	China RoHS declaration
	Pro-active China RoHS declaration (out of China RoHS legal scope)
Circularity Profile	End of Life Information