

TeSys D reversing contactor - 3P(3 NO) - AC-3 - <= 440 V 32 A - 100 V DC coil

LC2D32KD

! Discontinued

Main

Mairi	
Range	TeSys
Product Name	TeSys D
Product Or Component Type	Reversing contactor
Device Short Name	LC2D
Contactor Application	Resistive load
- Commercial Application	Motor control
Utilisation Category	AC 4
othisation category	AC-1 AC-3
Device Presentation	Preassembled with reversing power busbar
Poles Description	3P
Power Pole Contact Composition	3 NO
[Ue] Rated Operational Voltage	Power circuit: <= 690 V AC 25400 Hz
	Power circuit: <= 300 V DC
[le] Rated Operational Current	32 A (at <60 °C) at <= 440 V AC AC-3 for power circuit
[io] Nated Operational Current	50 A (at <60 °C) at <= 440 V AC AC-3 for power circuit
Motor Power Kw	7.5 kW at 220230 V AC 50 Hz
	15 kW at 380400 V AC 50 Hz 15 kW at 415440 V AC 50 Hz
	18.5 kW at 500 V AC 50 Hz
	18.5 kW at 660690 V AC 50 Hz
Motor Power Hn (III / Coa)	2 ha at 445 V AC CO Lie for 4 whose maters
Motor Power Hp (UI / Csa)	2 hp at 115 V AC 60 Hz for 1 phase motors
	5 hp at 230/240 V AC 60 Hz for 1 phase motors 7.5 hp at 200/208 V AC 60 Hz for 3 phases motors
	10 hp at 230/240 V AC 60 Hz for 3 phases motors
	20 hp at 460/480 V AC 60 Hz for 3 phases motors
	30 hp at 575/600 V AC 60 Hz for 3 phases motors
Operators I Olivers it Towns	· · · · · · · · · · · · · · · · · · ·
Control Circuit Type	DC standard
[Uc] Control Circuit Voltage	100 V DC
Auxiliary Contact Composition	1 NO + 1 NC
[Uimp] Rated Impulse Withstand Voltage	6 kV conforming to IEC 60947
Overvoltage Category	III
[Ith] Conventional Free Air	10 A (at 60 °C) for signalling circuit
Thermal Current	50 A (at 60 °C) for power circuit
Irms Rated Making Capacity	140 A AC for signalling circuit conforming to IEC 60947-5-1
	250 A DC for signalling circuit conforming to IEC 60947-5-1
	550 A at 440 V for power circuit conforming to IEC 60947
Rated Breaking Capacity	550 A at 440 V for power circuit conforming to IEC 60947

Age Ad Y C 10 stor power circuit		
280 A d 7C - 10 s for power circuit 480 A d 10°C - 1 s for power circuit 100 A - 1 s for signalling circuit 100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 153 A gG at <- 680 V coordination type 1 for power circuit 153 A gG at <- 680 V coordination type 1 for power circuit 153 A gG at <- 680 V coordination type 2 for power circuit 150 V CSA certified 150 V CSA CERTIF	[Icw] Rated Short-Time Withstand	60 A 40 °C - 10 min for power circuit
430 A 0°C - 1 s for power circuit 100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A g g of resignalling circuit conforming to IEC 60947-5-1 63 A g G at - 690 V coordination type 1 for power circuit 140 A g of signalling circuit 600 V coordination type 2 for power circuit 140 A g of signalling circuit 600 V coordination type 2 for power circuit 140 A g of signalling circuit 600 V coordination type 2 for power circuit 140 A g of signalling circuit 600 V coordination type 2 for power circuit 140 A g of signalling circuit 600 V coordination type 2 for power circuit 140 A g of signalling circuit 600 V coordination type 2 for power circuit 140 A g of signalling circuit 600 V coordination type 2 for power circuit 140 A coordination of the circuit 600 V coordination type 2 for power circuit 600 V coordination type 2 for pow	Current	138 A 40 °C - 1 min for power circuit
100 A - 1s for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 153 A gG at <= 680 V coordination type 1 for power circuit 63 A gG at <= 680 V coordination type 1 for power circuit 83 A gG at <= 680 V coordination type 2 for power circuit 84 Average Impedance 2 mOhm - Ith 50 A 50 Hz for power circuit 85 A gG at <= 680 V coordination type 2 for power circuit 86 A gG at <= 680 V coordination type 2 for power circuit 87 Average Impedance 2 mOhm - Ith 50 A 50 Hz for power circuit 88 Average Impedance 101 Rated Insulation Voltage Power circuit 600 V CSA certified Power circuit 600 V CSA certified Power circuit 600 V CSA certified Signalling circuit 600 V CSA certified S		·
120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit 140 A - 100 ms for signalling circuit conforming to IEC 60947-5-1 63 A gG at <= 690 V coordination type 1 for power circuit 43 A gG at <= 690 V coordination type 2 for power circuit 44 Average Impedance 2 mOhm - 1th 50 A 50 Hz for power circuit 44 Average Impedance 2 mOhm - 1th 50 A 50 Hz for power circuit 45 A gG at <= 690 V coordination type 2 for power circuit 46 A gG at <= 690 V coordination type 2 for power circuit 46 Average Impedance 2 mOhm - 1th 50 A 50 Hz for power circuit 46 A 2 control and a good and a g		·
Associated Fuse Rating 63 A gG at <= 690 V coordination type 1 for power circuit 63 A gG at <= 690 V coordination type 2 for power circuit 63 A gG at <= 690 V coordination type 2 for power circuit 63 A gG at <= 690 V coordination type 2 for power circuit 63 A gG at <= 690 V coordination type 2 for power circuit 64 Average Impedance 2 mOhm - Ith 50 A 50 Hz for power circuit 690 V CSA cortified Signalling circuit 690 V CSA cortified Power circuit: 690 V CSA cortified Signalling circuit: 590 V CSA cortified Signalling circ		ů ů
Associated Fuse Rating 10 A gG for signalling circuit conforming to IEC 60947-5-1 83 A gG at <= 690 V coordination type 1 for power circuit 83 A gG at <= 690 V coordination type 2 for power circuit 83 A gG at <= 690 V coordination type 2 for power circuit 83 A gG at <= 690 V conforming to IEC 60947-4-1 Power circuit: 690 V CSA certified Power circuit: 690 V CSA certified Signalling circuit: 690 V V CSA certified Signalling circuit: 690 V V Conforming to IEC 60947-4-1 Power circuit: 690 V V CSA certified Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V Conforming to IEC 60947-1 Signalling circuit: 690 V Conforming to IEC 60947-1 Signalling circuit: 690 V Conforming to IEC 60947-4 Signalling circuit: 690 V Conforming to IEC 60947-6 Signalling circuit: 690 V Conforming to IEC 60947-6 Signalling cir		· · ·
83 A gG at <= 690 V coordination type 1 for power circuit 83 A gG at <= 690 V coordination type 2 for power circuit 83 A gG at <= 690 V coordination type 2 for power circuit 890 V conforming to IEC 60947-4-1 Power circuit: 690 V CSA certified Power circuit: 600 V LSA certified Signalling circuit: 600 V SA certified Signalling ci		140 A - 100 ms for signalling circuit
Average Impedance 2 mOhm - Ith 50 A 50 Hz for power circuit 2 mOhm - Ith 50 A 50 Hz for power circuit 2 mOhm - Ith 50 A 50 Hz for power circuit 2 mOhm - Ith 50 A 50 Hz for power circuit 2 mOhm - Ith 50 A 50 Hz for power circuit 2 mOhm - Ith 50 A 50 Hz for power circuit 3 planiling circuit: 600 V CSA certified 5 signalling circuit: 600 V CSA certified 5 signalling circuit: 600 V CSA certified 5 signalling circuit: 600 V U. certified 5 signalling circuit: 600 V U. certified 5 signalling circuit: 600 V U. certified 6 signalling circuit: 600 V U. certified 7 signalling circuit: 600 V U. certified 6 signalling circuit: 600 V U. certified 6 signalling circuit: 600 V U. certified 7 signalling circuit: 600 V U. certified 6 signalling circuit: 600 V U. certified 7 signalling circuit: 600 V U. certified 8 signalling circuit: 600 V U. certified 9 signalling circuit: 600 V U. certified 8 s	Associated Fuse Rating	
Average Impedance 2 mOhm - Ith 50 A 50 Hz for power circuit 4 power circuit: 690 V CSA certified Power circuit: 690 V CSA certified Power circuit: 690 V CSA certified Signalling circuit: 690 V CSA certified Signalling circuit: 690 V V Conforming to IEC 69947-41 Power circuit: 690 V V Conforming to IEC 69947-1 Signalling circuit: 690 V V Conforming to IEC 69000000 V V color circuit: 690 V V Conforming to IEC 69000000 V V Conforming to IEC 690000000 V V Conforming to IEC 6900		
Power circuit: 690 V Conforming to IEC 60947-4-1 Power circuit: 690 V Conforming to IEC 60947-4-1 Power circuit: 690 V CSA certified Power circuit: 690 V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V Conforming to IEC 60947-1 Signalling circuit: 690 V V L certified Signalling circuit: 690 V L Certifie		63 A gG at <= 690 V coordination type 2 for power circuit
Power circuit: 600 V LOSA certified Power circuit: 600 V LOSA certified Signalling circuit: 600 V CSA certified Signalling circuit: 600 V CSA certified Signalling circuit: 600 V CSA certified Signalling circuit: 600 V LO certified Signalling circuit: 600 V LO certified Signalling circuit: 600 V LO certified 1.65 Mcycles 32 A AC-3 at Ue <= 440 V 1.4 Mcycles 50 A AC-1 at Ue <= 440 V 1.4 Mcycles 50 A AC-1 at Ue <= 440 V 1.4 Mcycles 50 A AC-1 at Ue <= 440 V 1.4 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 440 V 1.5 Mcycles 50 A AC-1 at Ue <= 4	Average Impedance	2 mOhm - Ith 50 A 50 Hz for power circuit
Power circuit: 600 V UL certified	[Ui] Rated Insulation Voltage	· · · · · · · · · · · · · · · · · · ·
Signaling circuit: 600 V DL certified Signaling circuit: 600 V UL certified 1.65 Mcycles 50 A AC-3 at Ue <= 440 V 1.4 Mcycles 50 A AC-1 at Ue <= 440 V Power Dissipation Per Pole 2. W AC-3 5. W AC-1 Front Cover With Interiocking Type Mechanical Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 60947-6-1 EC 60947-6-1 EC 60947-6-1 EC 60947-6-1 EC 60947-6-1 EC 60947-6-1 EC 60947-6-1 UL 508 Product Certifications CSA LROS (Lloyds register of shipping) GL CCC GOST UL BY N N N N N N N N N N N N N N N N N N		
Signalling circuit: 600 V CSA certified		
Signalling circuit: 600 V UL certified		
1.4 Mcycles 50 A AC-1 at Ue <= 440 V Power Dissipation Per Pole 2 W AC-3 5 W AC-1 Front Cover With Mechanical Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 60947-5-1 IEC 60947-6-1 IEC 60947-6-		
1.4 Mcycles 50 A AC-1 at Ue <= 440 V Power Dissipation Per Pole 2 W AC-3 5 W AC-1 Front Cover With Mechanical Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 60947-5-1 IEC 60947-6-1 IEC 60947-6-	Electrical Durability	1.65 Mcvcles 32 A AC-3 at Ue <= 440 V
Front Cover With Interlocking Type Mechanical Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-6-1 IEC 60947-6 IEC 609	•	· · · · · · · · · · · · · · · · · · ·
Front Cover With Interlocking Type Mechanical Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 80947-4-1 EN 60947-4-1 EIC 60947-4-1 EIC 60947-5-1 UL 508 Product Certifications CSA LROS (Lloyds register of shipping) GL CCC GOST UL BV DNV RINA Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable en	Power Dissipation Per Pole	2 W AC-3
Mounting Support Rail Plate Standards CSA C22.2 No 14 EN 80947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 IUL 508 Product Certifications CSA IROS (Lloyds register of shipping) GL CCC GOST UL BV DNV RINA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 3 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 3 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 4 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 5 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 5 c		
Rail Plate	Front Cover	With
Plate Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 UL 508 Product Certifications CSA LROS (Lloyds register of shipping) GL CCC GOST UL BY DNV RINA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm*flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm*solid Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid Control circuit: screw clamp terminals 2 cable(s) 14 mm*solid Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid Power circuit: screw clamp terminals 2 cable(s) 14 mm*solid Control circuit: screw clamp terminals 1 cable(s) 14 mm*solid Power circuit: screw clamp terminals 2 cable(s) 14 mm*solid Control circuit: screw clamp terminals 2 cable(s) 14 mm*solid Power circuit: screw clamp terminals 2 cable(s) 14 mm*solid Power circuit: screw clamp terminals 2 cable(s) 14 mm*solid Control circuit: screw clamp terminals 2 cable(s) 14 mm*solid Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm*flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm*solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm*solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm*solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm*solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm*solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm*solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm*solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm*solid Power circuit: screw cla	Interlocking Type	Mechanical
Standards CSA C22.2 No 14 EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 Product Certifications CSA LROS (Lloyds register of shipping) GL CCC GOST UL BY DNV RINA Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 110 mm²solid Power circuit: screw clamp terminals 1 cable(s) 110 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 ca	Mounting Support	Rail
EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 Product Certifications CSA LROS (Lloyds register of shipping) GL CCC GOST UL BV DNV RINA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 110 mm²slexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²solid end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø		Plate
EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 CSA LROS (Lloyds register of shipping) GL CCC GOST UL BV DNV RINA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on scre	Standards	CSA C22.2 No 14
IEC 60947-6-1 UL 508		EN 60947-4-1
IEC 60947-5-1 UL 508		
Product Certifications CSA LROS (Lloyds register of shipping) GL CCC GOST UL BV DNV RINA Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²solid Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Derating Time 53.5572.45 ms closing 1624 ms opening		
LROS (Lloyds register of shipping) GL CCC GOST UL BV DNV RINA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw c		
LROS (Lloyds register of shipping) GL CCC GOST UL BV DNV RINA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: 2.5 n.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw c	Product Certifications	CSV
GL CCC GOST UL BV DNV RINA Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	Trouder oct inications	
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
UL BV DNV RINA Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw		GOST
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 cable(s) 2.510 mm²solid Power circuit: 2.5 no screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips		UL
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 12 5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 2.5 ncm con screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit:		
Connections - Terminals Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 14 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible with cable end Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminal		KINA
Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible with cable end Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	Connections - Terminals	Control circuit: screw clamp terminals 1 cable(s) 14 mm²flexible without cable end
Control circuit: screw clamp terminals 2 cable(s) 12.5 mm²flexible with cable end Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		. , , ,
Control circuit: screw clamp terminals 1 cable(s) 14 mm²solid Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 200000000 cycles contactor with mechanical load conforming to EN/ISO		. , , ,
Control circuit: screw clamp terminals 2 cable(s) 14 mm²solid Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		. , , ,
Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
end Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		. , , ,
Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²flexible without cable end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
end Power circuit: screw clamp terminals 1 cable(s) 110 mm²flexible with cable end Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Power circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 2 cable(s) 1.56 mm²flexible with cable end Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 1 cable(s) 1.510 mm²solid Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: screw clamp terminals 2 cable(s) 2.510 mm²solid Tightening Torque Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Operating Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		. , ,
Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Control circuit: 1.7 N.m - on screw clamp terminals - with screwdriver Philips No 2 Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 53.5572.45 ms closing 1624 ms opening B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver flat Ø 6 mm Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Departing Time 53.5572.45 ms closing 1624 ms opening Bafety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	lightening Torque	·
Power circuit: 2.5 N.m - on screw clamp terminals - with screwdriver Philips No 2 Description: 53.5572.45 ms closing 1624 ms opening Bafety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		
Dperating Time 53.5572.45 ms closing 1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		·
1624 ms opening Safety Reliability Level B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO	Operating Time	<u> </u>
B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO		•
	Safety Reliability Level	B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1
IVUTV'I		
		10010-1

Maximum Operating Rate 3600 cyc/h 60 °C

Complementary

•	
Coil Technology	Built-in bidirectional peak limiting diode suppressor
Control Circuit Voltage Limits	0.10.25 Uc (-4070 °C):drop-out DC 0.71.25 Uc (-4060 °C):operational DC 11.25 Uc (6070 °C):operational DC
Time Constant	28 ms
Inrush Power In W	5.4 W (at 20 °C)
Hold-In Power Consumption In W	5.4 W at 20 °C
Auxiliary Contacts Type	type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1 type mirror contact 1 NC conforming to IEC 60947-4-1
Signalling Circuit Frequency	25400 Hz
Minimum Switching Current	5 mA for signalling circuit
Minimum Switching Voltage	17 V for signalling circuit
Non-Overlap Time	1.5 ms on de-energisation between NC and NO contact 1.5 ms on energisation between NC and NO contact
Insulation Resistance	> 10 MOhm for signalling circuit

Environment

Ip Degree Of Protection	IP20 front face conforming to IEC 60529
Protective Treatment	TH conforming to IEC 60068-2-30
Pollution Degree	3
Ambient Air Temperature For Operation	-4060 °C 6070 °C with derating
Ambient Air Temperature For Storage	-6080 °C
Operating Altitude	03000 m
Fire Resistance	850 °C conforming to IEC 60695-2-1
Flame Retardance	V1 conforming to UL 94
Mechanical Robustness	Vibrations contactor open: 2 Gn, 5300 Hz Vibrations contactor closed: 4 Gn, 5300 Hz Shocks contactor closed: 15 Gn for 11 ms Shocks contactor open: 8 Gn for 11 ms
Height	85 mm
Width	90 mm
Depth	101 mm
Net Weight	1.127 kg

Contractual warranty

Warranty 18 months