



Main

| | |
|---------------------------|-------------------|
| Range | TeSys |
| Device short name | LUA1 |
| Product or component type | Auxiliary contact |

Complementary

| | |
|---|--|
| Auxiliary contact composition | 1 NO + 1 NC |
| Signalling function | Indicating rotary knob in ready position Fault signalling |
| [Ue] rated operational voltage | <= 250 V AC <= 250 V DC |
| [Ui] rated insulation voltage | 250 V conforming to CSA 250 V conforming to IEC 60947-5-1 250 V conforming to UL |
| [Ith] conventional free air thermal current | 5 A |
| Minimum switching voltage | 17 V |
| Minimum switching current | 5 mA |
| Product weight | 0.012 kg |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

LUA1C110 is replaced by:



Auxiliary contacts LUA1C11
signalling contacts LUA - 1 NO + 1 NC

Qty 1

Reason for Substitution: End of Life | Substitution date: 24 November 2005